



## DESCRIPTION

### Open programmable compact safety control

- integrated movement monitoring for up to 2 axes
- 6 Encoder interfaces (one with safePXV-encoder interface)
- 14 safe digital inputs
- 2/4 pn- or pp- switching outputs
- 2 Auxiliary / pulse outputs
- Safety controller up to PL e acc. to EN ISO 13849-1 or SIL3 acc. to IEC 61508
- optional: safe/non-safe fieldbus interface

## CHARACTERISTIC OF THE MODULE

- » Extendable up to:
  - max. 42 safe digital inputs,
  - max. 12 safe digital outputs,
  - max. 20 safe digital I/O's,
  - max. 9 safe relay outputs,
  - max. 10 auxiliary outputs,
  - max. 2 safe axes
- » Freely programmable for the safe processing of Emergency stop buttons, two-hand operation, Light grids, mode selectors, etc.
- » Complete speed and position-related safety functions for drive monitoring IEC 61800-5-2 integrated into firmware
- » Safe position monitoring with only one sensor in combination with the optical reading head PXV100AS-F200-R4-V19-BBH
- » Speed monitoring
- » Standstill monitoring
- » Direction monitoring
- » Safe incremental dimension
- » Emergency Stop monitoring
- » Position monitoring
- » Position range monitoring
- » Trend range monitoring
- » Target position monitoring
- » Logic diagram oriented programming via SafePLC<sup>2</sup>
- » Pulse outputs for cross-shortening detection of digital input signals
- » External contact monitoring of connected switchgear (EMU)
- » Switchable safe semi-conductor outputs pn-, pp- switching for safety-relevant functions

# SMX 12-1-PXV/2/x

SMXSERIES » Compact » Basic modules

**BBH**  
PRODUCTS

- » Monitored relay outputs for safety relevant functions
- » Comprehensive diagnostics functions integrated
- » Parameter management for expansion modules in base device
- » Coded status display via front-side 7 segment display and status LEDs
- » Multifunction buttons (quit, start, reset) can be operated from the front side
- » Configurable via SafePLC<sup>2</sup> über USB serial adapter or ethernet based field bus
- » Extended functionality: SafePXV-encoder interface
- » Integrated Memory Card
- » Extended functionality:
  - allows the connection of 2 rotary encoder per axis (SSI-Absolut, Sin/Cos,TTL, HTL proximity switch)
  - 2. encoder interface also support HTL (200 kHz), Sin/Cos High-Resolution and Resolver
- » Optional: integrated Communication interface :
  - Standard and safe field bus protocols for communication with a higher level controller (PROFIBUS, PROFINET, DeviceNet, CANopen, EtherNET/IP, EtherCAT, Modbus TCP, PROFIsafe, FSoE)
  - Safe cross communication (SMMC) for data exchange between multiple base devices
  - Field bus protocols with the same hardware can be switched with SafePLC<sup>2</sup>
  - Safe remote I/O communication for data exchange with distributed I/O systems
- » The mechanical structure of SMX12-1-PXV/2 (x\*) is depended on the respective form of the base module

\* *Optional: integrated communication interface (/DNM, /DBM)*

BBH PRODUCTS GMBH

Böttgerstraße 40  
D- 92637 Weiden

Tel.: + 49 961/4 82 44-0  
Fax: + 49 961/4 82 44-35

[www.bbh-products.de](http://www.bbh-products.de)

[contact@bbh-products.de](mailto:contact@bbh-products.de)

**SAFETY @ ITS BEST!**

## SAFETY RELATED CHARACTERISTIC DATA

Performance Level	PL e (EN ISO 13849-1)
PFH / architecture	12,6 FIT / Cat 4
Safety Integrity Level	SIL 3 (IEC 61508)
Proof test interval	20 years = max. operating period

## GENERAL DATA

Max. no. of expansion modules	2
Interface for expansion modules	T-bus connector, pluggable in top-hat rail RJ-45 (Ethernet)
Number of safe digital inputs	14
Number of safe digital outputs	
	pp-switching ** 4
	pn-switching ** 2
Number of safe digital I/O	-
Number of relay outputs	2
Number of safe analogue inputs	-
Number of auxiliary outputs	2
Number of pulse outputs (clock outputs)	2
Type of connection	Plug-in terminals with spring or screw connection
Axis monitoring (axes / encoder interfaces)	2 / 6 *
Encoder technology (D-Sub / Screw terminals / RS 485)	<p><b>D-SUB X31:</b> SSI-Absolut, SinCos, Incremental-TTL</p> <p><b>D-SUB X33:</b> SSI-Absolut, SinCos, SinCos (HighRes), Incremental-TTL, Resolver</p> <p><b>Terminal X23:</b> HTL-proximity sensor (10kHz)</p> <p><b>Terminals X27, X28:</b> Incremental-HTL (200kHz)</p> <p><b>RS 485, X35:</b> PXV100AS-F200-R4-V19-BBH</p>

\* maximum 2 encoder / axis

\*\* pn/pp are configurable via SafePLC<sup>2</sup>



## ELECTRICAL DATA

Supply voltage (tolerance)		24 VDC; 2A (-15%, +20%)
Fuse	X11.1	min. 30 VDC; max. 3,15A
	X11.2	min. 30 VDC; max. 10A
Max. Power consumption (logic)		
	SMX12-1-PXV/2	4,8 W
	SMX 12-1-PXV2/x	7,2 W
Rated data digital inputs		24 VDC; 20 mA Typ1 acc. to IEC 61131-2
Rated data digital outputs		
	pn-switching	24 VDC; 2A *
	pp-switching	24 VDC; 2A *
	auxiliary outputs	24 VDC; 250mA
	pulse outputs (clock outputs)	24 VDC; 250mA
Rated data relays		
Normally open	DC 13	24 VDC; 2A
	AC 15	230 VAC; 2A

\* See „Derating Outputs“

## DERATING OUTPUTS

- » Maximum current load based on temperature
- » The maximum total current is 10A

type of module	outputs	temperature 30°C / 50°C
SMX1x/2/x	Q 1 – Q 4	2A / 1,8A

## ENVIRONMENTAL DATA


Temperature	0°C ... +50°C operation -25°C ... +70°C storage and transport
Class of protection	IP 20
Climatic category	3K3 acc. to DIN EN 60721-3
Min-, Maximum relative humidity (no condensation)	5% - 85%
EMC	DIN EN 61000-6-2, DIN EN 61000-6-4, DIN EN 61000-6-7, DIN EN 61800-3
Operating altitude	2000m

## MECHANICAL DATA

Dimensions (HxDxW [mm])	SMX12-1-PXV/2	100x115x90
	SMX12-1-PXV/2/x *	100x115x112,5
Weight [g]	SMX12-1-PXV/2	520
	SMX12-1-PXV/2/x *	620
Mounting	auf Normschiene aufschraubbar	
Number of T-Bus	SMX12-1-PXV/2	4
	SMX12-1-PXV/2/x *	5
Min. terminal cross-section / AWG	0,2 mm <sup>2</sup> / 24	
Max. terminal cross-section / AWG	2,5 mm <sup>2</sup> / 12	

\* Specification, see: „Optional integrated communication interface“

## DEVICE INTERFACES



Schnittstelle	Kurzbeschreibung
X11 – X17 / X21 – X24 / X41 / X81	Voltage supply and I/O interface
SDHC	Memory Card for safety program
COM	Diagnostic- and configuration interface
X91 / X92	Decentralized SDDC ETH and SMMC interface
X93 / X94	Field bus interfaces
X23 / X27 / X28	Encoder interface
X31 / X33 / X35	Encoder interface

## VOLTAGE SUPPLY AND I/O INTERFACE

X 11		
Pin	1 - A1.1	Voltage supply device +24 VDC
	2 - A1.2	Voltage supply device +24 VDC outputs
	3 - A2.1	Voltage supply device 0 VDC
	4 - A2.2	Voltage supply device 0 VDC
X 12		
Pin	1 - I13	Safe digital inputs
	2 - I14	
	3 - T1	Clock outputs
	4 - T2	

X 13		
Pin	1 – UE1+	Voltage supply Encoder +24V DC X31
	2 – UE1-	Voltage supply Encoder 0V DC X31
	3 - Y1	Auxiliary outputs
4 - Y2		
X 14		
Pin	1 - I01	Safe digital inputs
	2 - I02	
	3 - I03	
	4 - I04	

X 17		
Pin	1 - UE3+	Voltage supply Encoder +24V DC X33
	2 - UE3-	Voltage supply Encoder 0V DC X33
	3 - UR3	Referenzspannung Encoder X33
	4 - NC	No function
X 21		
Pin	1 - Q1	Output of the pn-switching Q1_PP / pp-switching Q1
	2 - Q2	Output of the pn-switching Q2_PN / pp-switching Q2
	3 - Q3	Output of the pn-switching Q3_PP / pp-switching Q3
	4 - Q4	Output of the pn-switching Q4_PN / pp-switching Q4
X 22		
Pin	1 - Q5.1	Safe relay output
	2 - Q5.2	
	3 - Q6.1	Safe relay output
	4 - Q6.2	

X 23		
Pin	1 - I05	Safe digital inputs
	2 - I06	
	3 - I07	
	4 - I08	
X 24		
Pin	1 - I09	Safe digital inputs
	2 - I10	
	3 - I11	
	4 - I12	
X 41		
Pin	1 - A 1.3	Voltage supply Sensor +24 VDC
	2 - A 1.4	
	3 - A 2.3	Voltage supply Sensor 0 VDC
	4 - A 2.4	
X 81 *		
Pin	1 - SD_BUS_24V	Power supply SD-BUS +24 VDC
	2 - SD_BUS_GND	Power supply SD-BUS 0 VDC
	3 - SD_BUS_OUT	SD-BUS Output
	4 - FUNC_EARTH	Funktional Earth

\* Only available for field bus variants

## DIAGNOSTIC AND CONFIGURATION INTERFACE

### Pin assignment

RJ 10, 4-pin		
Pin	Description	COM front side
1	GND	
2	RS485-	
3	RS485+	
4	VCCH	

» With existing Ethernet-based fieldbus interface, it can be used as a diagnostic and configuration interface.



## DECENTRALIZED SDDC ETH AND SMMC INTERFACE

### Pin assignment female connector

Communication interface (RJ45-Buchse)				Front side
Pin	Name	Description	Colour	X91 / X92
1	TX+	Transmit Data +	white-orange	
2	TX-	Transmit Data -	orange	
3	RX+	Receive Data +	white-green	
4	nc	not used	blue	
5	nc	not used	white-blue	
6	RX-	Receive Data -	green	
7	nc	not used	white-brown	
8	nc	not used	brown	

### Safe Master – Master Communication (SMMC)

SMMC communication enable a secure data exchange of 2 bytes between multiple SDDC masters. Communication takes place without a master for coordinating the data. This means that data exchange between available subscribers is always possible. This principle means that an incomplete or separates network can work in part areas without chnaging the configuration.

Each port can be configured in the SafePLC<sup>2</sup>.

## FIELDBUS INTERFACES

### Pin assignment female connector

Ethernet-based fieldbus interface /xNx (RJ45)				Front side
Pin	Name	Description	Colour	X93 / X94
1	TX+	Transmit Data +	white-orange	
2	TX-	Transmit Data -	orange	
3	RX+	Receive Data +	white-green	
4	nc	not used	blue	
5	nc	not used	white-blue	
6	RX-	Receive Data -	green	
7	nc	not used	white-brown	
8	nc	not used	brown	

CAN-based fieldbus interface /DBM, /xBM (D-Sub)				Front side
Pin	CANopen	PROFIBUS	DeviceNet	
1	—	—	V-	
2	CAN_L	—	CAN_H	
3	isoGND	RXD/TXD-P (B)	DRAIN	
4	—	CNTR-P	CAN_L	
5	—	GND	V+	
6	—	VP (+5V)	—	
7	CAN_H	—	—	
8	—	RXD/TXD-N (A)	—	
9	—	CNTR-N	—	



## OPTIONAL INTEGRATED COMMUNICATION INTERFACE

- » Subsequent expansion capability of standard to safe field bus via additional Mini SD card on the back of the module is possible (/xNx und /xBx)
- » Different specifications can be combined

### General data

Decentralized communication interface	
/D	2x RJ 45 *
Fieldbus interface	
/xN	2x RJ 45 **
/xB	1x Sub-D ***
MemoryCard (safety program)	
/xxM	1x Mini SD (front side)
Memory Card (license for safe field bus)	
/xNx	1x Mini SD (rear side)
/xBx	
SD bus	plug-in terminals
Status LEDs	4
Field bus adress rotary switch	
/xBx	2

\* optional for SDDC or SMMC

\*\* available field buses PROFINET, EtherCAT, Modbus TCP and Ethernet TCP/IP

\*\*\* available field buses PROFIBUS, CANopen und DeviceNet

### Combination options

	/D	/DNM	/xNM	/xxM	/DBM	/xBM
--	----	------	------	------	------	------

Field bus protocols	/DBM	/xBM	/DNM	/xNM
PROFIBUS	X	X		
DeviceNet	X	X		
CANopen	X	X		
PROFINET			X	X
Ethernet IP			X	X
EtherCAT			X	X
Modbus TCP			X	X
PROFIsafe *	X	X	X	X
FSoE *			X	X

\* Specification required in your order

» The CAN-based and Ethernet-based fieldbus interfaces can be switched via the SafePLC<sup>2</sup> between the fieldbus protocols

## ENCODER INTERFACES

### Pinassignments X31 , X33

Pin	X31 Inc / Sin/Cos / SSI	X33 Inc / Sin/Cos / SSI	X33 Resolver	Front side SMX
1	n.c.	n.c.	Ref_Out +	
2	GND_ENC	GND_ENC	GND_ENC	
3	n.c.	n.c. / n.c. / Clk +	Ref_In +	
4	B- / COS - / Clk -	B- / COS - / n.c.	COS -	
5	A+ / SIN + / Data +	A+ / SIN + / Data +	SIN +	
6	A- / SIN - / Data -	A- / SIN - / Data -	SIN -	
7	n.c.	n.c. / n.c. / Clk -	Ref -	
8	B+ / COS + / Clk +	B+ / COS + / n.c.	COS +	
9	U_ENC	U_ENC	U_ENC	

### Pinassignments X23 , X27 , X28 / X35

Pin	Z1 – Z1 / Z2 – Z2	Terminals
1	A ( $\bar{A}$ ) / A ( $\bar{A}$ )	
2	-- / B ( $\bar{B}$ )	
3	A ( $\bar{A}$ ) / A ( $\bar{A}$ )	
4	-- / B ( $\bar{B}$ )	

Pin	A+/A-	A+ Signal	Terminals
1 – H1A	A+	24V	
2 – H2A	A-	A	
3 – H3A	A+	GND	
4 – NC	—	—	

Pin	B+/B-	B+ Signal	Terminals
1 – H1B	B+	24V	
2 – H2B	B-	B	
3 – H3B	B+	GND	
4 – NC	—	—	

Pin	RS 485	Front side SMX
1	Enable Blue	
2	UB+	
3	Data +	
4	Data -	
5	Sync IN	
6	Enable Red	
7	GND	
8	NC	

## ENCODER SPECIFICATIONS

### PXV100AS-F200-R4-V19-BBH

Physical Layer	RS-485 compatible
Data format	Binary Code
Transmission rate	115200 Bit/s
Type of connection (X35)	male connector 1x M12, 8-pin
Termination	120 $\Omega$ , selectable

#### General data

Overrun speed v	$\leq 10$ m/s
Measuring length	max. 100000 m
Resolution	$\pm 1$ mm
Measuring frequency	100 Hz

### Inkremental - TTL

Physical Layer	RS-422 compatible
Measuring signal A/B	Track with 90 degree phase difference
Type of connection	D-SUB 9-pole
Max. frequency of input cycles (X31 / X33)	200 kHz / 250 kHz

### Sin/Cos

Physical Layer	RS-422 compatible
Measuring signal A/B	Track with 90 degree phase difference
Type of connection	D-SUB 9-pole

#### Standard Mode

Max. frequency of input clock pulses (X31 / X33)	200 kHz / 250 kHz
--	-------------------

#### High Resolution Mode

Max. frequency of input cycles (X33)	15 kHz
--------------------------------------	--------

### SSI-Absolut

Data interface	<b>Serial Synchronous Interface (SSI)</b> with variable data length of 12 – 28 Bit
Data format	Binary, Gray code
Physical Layer	RS-422 compatible
Type of connection	D-SUB 9-pole
<b>Mode</b>	<b>Master oder Listener</b>

#### SSI-Master operation

Clock rate	150 kHz
------------	---------

#### SSI-Listener operation

Clock rate (X31 / X33)	100 kHz ... 200 kHz / 100 kHz ... 250 kHz
Min. clock pause time	150 $\mu$ sec
Max. clock pause time	1 msec



# SMX 12-1-PXV/2/x

SMXSERIES » Compact » Basic modules

**BBH**  
PRODUCTS

## Resolver

Measuring signal	Sin/Cos – track with 90° phase difference
Signal frequency	max. 600 Hz (900Hz Deep pass)
Input voltage	max. 8 Vss (an 16 kΩ)
Resolution	9 Bit / pole
Supported pole number	2 - 16
<b>Mode</b>	<b>Master oder Listener</b>
<b>Resolver-Master operation</b>	
Reference frequency	8 kHz
<b>Resolver-Listener operation</b>	
Reference frequency	4 kHz – 16 kHz
Reference amplitude	8 Vss – 28 Vss
Reference signal form	Sinusoidal, triangle
Transformation ratio	2:1; 3:1; 4:1
Phase fault	max. 8°
Type of connection (X33)	D-SUB 9-pole

## Incremental - HTL

Signal level	24V / 0V
Physical Layer	PUSH / PULL
Max. counting pulse frequency	200 kHz
Type of connection (X27, X28)	Plug-in terminals with spring or screw connection

## HTL proximity sensor

Signal level	24V / 0V
Max. counting pulse frequency (circuit logic de-bounced)	10 kHz
Pulse width	50 µsec
Type of connection (X23)	Plug-in terminals with spring or screw connection

## HTL proximity switch - extended monitoring

Signal level	24V / 0V
Max. counting frequency (circuit logic de-bounced)	4 kHz
Physical Layer	PUSH / PULL
Measuring signal A/B	Track with 90 degree phase difference
Type of connection (X23)	Plug-in terminals with spring or screw connection

# SMX 12-1-PXV/2/x

SMXSERIES » Compact » Basic modules

## ORDER INFORMATIONS

### BASIC MODULES

item	description	item no.
SMX12-1-PXV/2	Basic module with integrated movement monitoring for up to 2 axes with extended encoder interface + safePXV-encoder interface	on request
SMX12-1-PXV/2/D	Basic module + decentralised communication	on request
SMX12-1-PXV/2/DNM	Basic module + decentralised communication + Ethernet-based field bus interface + Memory Card	2611
SMX12-1-PXV/2/xNM	Basic module + Ethernet-based field bus interface + Memory Card	2612
SMX12-1-PXV/2/xxM	Basic module + Memory Card	on request
SMX12-1-PXV/2/DBM	Basic module + decentralised communication + CAN-based field bus interface + Memory Card	on request
SMX12-1-PXV/2/xBM	Basic module + CAN-based field bus interface + Memory Card	on request

### ACCESSORIES

item	description	item no.
SMX91	Programming adapter SMX	1010
SXxxx-x	Terminal connector, screw terminals (set), encoded for cabling SMX12-1-PXV/2	on request
SXxxx-x	Terminal connector, spring terminals (set), encoded for cabling SMX12-1-PXV/2	on request
SX0000-9	T-Bus connector volltage-carrying (grey)	1015
SXxxx-x	Y-cable for encoder splitting	on request
FSoE License	Field bus license for FSoE	2366
PROFIsafe License	Field bus license for PROFIsafe	2319
PXV100AS-F200-R4-V19-BBH	Optical reading head for incident light positioning system	2581

### EXTENSIONS

item	description	item no.
SMX31/2	I/O expansion module	1705
SMX31R/2	I/O expansion module with relay option	2046
SMX31R-4/2	I/O expansion module with relay option	2047

### SOFTWARE

item	description	item no.
SafePLC <sup>2</sup> 1st	Programming software, 1te License incl. Hardlock	1244
SafePLC <sup>2</sup> 2nd	Programming software, 2te License incl. Hardlock	1646
SafePLC <sup>2</sup> 3rd	Programming software, 3te License incl. Hardlock	1647